

SN98660 Series

Multimedia Network Platform

Description

SONiX SN98660 Series is a highly integrated H.264 and MJPEG SoC solution. With hardwired video encoder architecture, the SN98660 Series operates at clock frequencies up to 402 MHz. The core is comprised of an ARM926EJ-S CPU with 16 KB I/D cache for computing multi-stream video encoding or image analysis in intelligent surveillance applications such as object detection. The H.264 encoder supports 1080p30 + 640p30, 720p30 + 720p30, or 720p30 + 640p30 multi-streams.

The SN98660 Series platforms integrate a wide range of essential components for multimedia embedded systems applications such as IP cameras, dash-cams, and wireless microscopes. The SN98660 Series includes H.264 encoder, MJPEG encoder, parallel/MIPI senor interface, ISP, serial flash, SD card, DDR2, I²S/ADPCM audio controller with Audio DAC and ADC, CRC-16 engine, USB 2.0 host and device, DMA, 10/100M Ethernet, and AMBA 2.0 bus framework.

The SN98660 Series is supported by Linux or RTOS based development environments making it suitable for various embedded multimedia applications and solutions.

Features

Hardware	Details		
CPU	ARM926EJ-S Processor 402 MHz with 16 KB I/D cache		
Memory	SiP DDR2 64 MB up to 402 MHz, 16-bit data bus		
ISP	Supports AE/AWB/AF/HDR and alpha-blending OSD		
	H.264 BP/MP/HP Level 4.1 and Baseline JPEG encode		
Video Codec	Rate control supporting Manual Region of Interest (MROI) with 8 Regions		
	Flexible multi-streaming		
Sensor Input Interface	Parallel data input (10-bits RAW and YUV 4:2:2)		
Concor input interface	MIPI CSI-2 with one data lane (800 Mbps)		
Sensor Resolution and	2048 x 1536 (3MP), 1600 x 1200 (UXGA, 2MP), 1920 x 1080 (FHD), 1280		
Format	x 1024 (SXGA, 1.3MP), 1280 x 720 (HD), 640 x 480 (VGA, 0.3MP) with		
	CMOS ISP/Bayer RAW sensors		
Audio codec	16-bit sigma-delta ADC and 10-bit R2R DAC		
Ethernet	One 10/100M EtherMAC with RMII interface		
USB	One USB 2.0 host controller, and one USB 2.0 device controller		
SD/SDIO	One SD/SDIO controller supports standard SD/SDIO 1.0/1.1/2.0		
35/3510	specification and is compatible with SD3.0 (SDXC)		
DMA Controller	Four channels that support memory to memory and memory to peripherals		
	transfers		
CRC-16	Hardware CRC-16 codec		
	CRC-16 with polynomial is $X^{16} + X^{15} + X^2 + 1$		
Peripheral	10 / 100M Ethernet media access controller		
	I ² C x 1, UART x 2, PWM x 3, GPIO x 3, SPI x 1, and Pinmux x 38		
	RTC, watchdog timer, Timer, and JTAG		
	Core: 1.14V to 1.26V (1.20V typical)		
Voltage	DRAM: 1.7V to1.9V (1.8V typical)		
	I/O: 3.0V to 3.6V (3.3V typical)		

www.sonix.com.tw 1 CG-BZZD-160728.2X



Functional Block Diagram

USB Host	USB Device	EtherMAC		SPI		
Sensor Input	ISP		Video Codec		Pinmux	
Interface					GPIO	
Serial Flash	ARM926DJ-S with 16 KB cache			5.10		
	DMA Controller		CRC-16		UART	
SD/SDIO	64MB DDR2		Audio Codec & I ² S			
	WDT/Timer	R	тс	I ² C	PWM	

Figure 1. Functional block diagram of SONiX SN98660 Series

Absolute Maximum Ratings

Parameter		Rating	Unit	
Supply voltage ranges	All 1.20V supplies	-0.30 to 1.30		
	All 1.80V supplies	-0.30 to 1.90		
	All 2.50V supplies	-0.30 to 2.75		
	All 3.30V supplies	-0.30 to 3.60	v	
Input voltage ranges	All 1.80V I/Os	-0.30 to 1.90		
	All 3.30V I/Os	-0.30 to 3.60		
Operating case temperature ranges (T _C)		0 to 70	°C	
Storage temperature ranges (T _{STG})		-40 to 150		

Note:

Electrical Characteristics

Parameter		Conditions		Limits		
		Conditions	Min	Тур	Max	Unit
Input Voltage	V _{IL}	all conditions	-0.30	_	0.80	V
	V _{IH}		2.00	_	3.60	
Output Voltage	V _{OL}	all conditions	_	_	0.40	
	V _{OH}		2.40	_	_	
Output Current	I _{OL_4mA}	V _{OL} = 0.45 V	4.8	7.1	9.4	- mA
	I _{OL_8mA}		9.8	14.4	19.1	
	I _{OL 12mA}		14.8	21.8	28.8	
	I _{OH_4mA}	V _{OL} = 2.40V	7.0	13.4	22.7	
	I _{OH_8mA}		13.9	26.8	45.2	
	I _{OH_12mA}		20.8	40.1	67.8	

Long-term exposure to absolute maximum ratings may affect device reliability, and permanent damage may occur if the operation exceeds the maximum ratings.
All voltage values are with respect to VSS



Packaging Dimensions

• SONIX SN98660/661 LQFP-128-EP (14 x 14 x 1.4 mm)




Figure 2. Package outline of SONiX SN98660 Series



TERMS AND CONDITIONS

- 1. Content: This Brief Data Sheet is intended for quick reference only and shall not be relied upon to contain detailed and full information. To obtain detailed and full information, contact appropriate SONiX representative or visit SONiX website at http://www.sonix.com.tw/masterpage-en. In the event of any inconsistency or conflict with the Brief Data Sheet, the Full Data Sheet shall prevail. While SONiX takes care to prepare this information, it may contain typographical errors or outdated technical information as SONiX will continue to update its integrated chip products with enhancements, improvements and other changes to better serve the needs of its customers. This Data Sheet covers products offered in Taiwan and may not reflect the products offered in other countries. Users of this Data Sheet should inquire of the appropriate SONiX representative to obtain the latest relevant information concerning the product (s) in question before placing their order. All SONiX's products are sold subject to SONiX's terms and conditions of sale that are supplied at the time of order.
- The information contained herein is presented only as a reference for product use. Unless No Warranty: expressly set forth otherwise, SONiX does not warrant or represent that any license, either express or implied, is granted by this Data Sheet relating to any combination, machine, or process in which SONIX products are used (or to be used). Information in this Data Sheet regarding third-party products is not a license for use of such products, or a warranty or endorsement thereof. No license to any intellectual property is granted by this document, whether express or implied, by estoppel or otherwise. Absent a written signed agreement or except as provided in the relevant terms and conditions of sale for the products, and to the maximum extent allowable by law, (1) SONIX ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION, AND LOSS OF DATA, AND (2) SONIX DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.
- 3. Customers' Use: SONIX ASSUMES NO LIABILITY FOR CUSTOMERS' PRODUCT DESIGNS OR APPLICATIONS of the products covered by the Data Sheet. While from time to time SONiX may be asked to assist users of its products, SONiX assumes no liability for assistance with, or the design of, users' own application of SONiX's products, including but not limited to: (a) determining the appropriateness of the use of SONiX products in the desired design or application; (b) evaluating and determining the applicability of any information contained in this Data Sheet, or in charts, diagrams, programs, algorithms, sample application circuits, or other referenced documents; and (c) validating all operating parameters for such designs and applications. Finally, SONIX products shall not be used for, or incorporated into, any products or systems whose manufacture, use, or sale is prohibited under any applicable laws or regulations.
- Improper & Unintended Use: SONIX'S PRODUCTS ARE NOT INTENDED NOR WARRANTED FOR USE IN EQUIPMENTS OR SYSTEMS THAT REQUIRE EXTRAORDINARILY HIGH LEVELS OF QUALITY OR RELIABILITY, OR A MALFUNCTION OR FAILURE OF WHICH MAY CAUSE LOSS OF HUMAN LIFE, BODILY INJURY, SERIOUS PROPERTY DAMAGE, OR SERIOUS PUBLIC IMPACT ("UNINTENDED USE"). Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the military or aerospace industry, medical equipment, equipment used for automobiles, trains, ships, and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators, and escalators, devices related to electric power, and equipment used in finance-related fields. Further, only those products that SONiX has specifically designated as "military grade" are designed and intended for use in military or aerospace applications or environments. acknowledge and agree that any military or aerospace use of SONiX products that have not been so designated is solely at the user's risk, and that the user is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

Headquarters

10, No.36, Taiyuan St., Chupei City, HsinChu, Taiwan

Tel: 886-3-5600-888

Email: info@sonix.com.tw; fae@sonix.com.tw

Hong Kong Office

Unit 2603, 26/F CCT Telecom Building, No.11 Wo Shing Street, Fo Tan, New Territories, Hong Kong Tel: 852-2723-8086

Email: hk@sonix.com.tw

Taipei Office

15F-2, No.171 Song Ted Rd., Taipei, Taiwan

Tel: 886-2-2759-1980

Email: mkt@sonix.com.tw; sales@sonix.com.tw

U.S.A Office

Tim Lightbody Orange County, CA, USA Tel: 1- (714) 330-9877

Email: tlightbody@earthlink.net